

A-2240

MIXER AMPLIFIER

Multi-purpose, multi-function mixer/power amplifiers specifically designed for maximum versatility and cost-effective high-performance are ideal units for any PA requirement in locations such as shops and offices and other small to intermediate sized environments. A choice of different power outputs are offered as well as as paging override of BGM.



Order no: A-2240 CE
Alternative products: A-2240

Specifications

Power source	220 - 240 V AC, 50 / 60 Hz (24 V DC)
Frequency response	50 Hz - 20 kHz (± 3 dB)
Distortion	< 1 % (at 1 kHz, 1/3 rated output power)
Current consumption	15 A (24 V DC, at rated output)
S/N ratio	60 dB (or more)
Connectable microphones	3
Inputs	MIC 1, 2, 3: -60dBV, 600 Ω , electronically balanced, MIC 1: DIN jack, MIC2&3: phone jack
Control input	Mute: contact input for MIC 1 at DIN jack (pins 4-5)
Outputs	for Recording: 0 dBV, 600 Ω , unbalanced, RCA jack
Dimensions (W x H x D)	420 x 100,9 x 280,3 mm
Dimensions (ϕ x D)	x 280,3 mm
Finish	ABS resin, Steel plate, black

A-2240

MIXER AMPLIFIER

Appearance

